

Linux From Scratch - Version 12.1-systemd		
Chapter 9. System Configuration		
	/	
Configuring the System Locale	Creating the /etc/shells File	

9.8. etc/inputrc

```

inputrc          가                               readline
               .                               . Readline  bash

/etc/inputrc    .
               .inputrc

inputrc        info bash                        Readline Init File
               . info readline
               .
               inputrc

```

```

cat > /etc/inputrc << "EOF"
# Begin /etc/inputrc
# Modified by Chris Lynn <roryo@roryo.dynup.net>

# Allow the command prompt to wrap to the next line
set horizontal-scroll-mode Off

# Enable 8-bit input
set meta-flag On
set input-meta On

# Turns off 8th bit stripping
set convert-meta Off

# Keep the 8th bit for display
set output-meta On

# none, visible or audible
set bell-style none

# All of the following map the escape sequence of the value
# contained in the 1st argument to the readline specific functions
"\e0d": backward-word
"\e0c": forward-word

# for linux console
"\e[1~": beginning-of-line

```

```
"\e[4~": end-of-line
"\e[5~": beginning-of-history
"\e[6~": end-of-history
"\e[3~": delete-char
"\e[2~": quoted-insert

# for xterm
"\eOH": beginning-of-line
"\eOF": end-of-line

# for Konsole
"\e[H": beginning-of-line
"\e[F": end-of-line

# End /etc/inputrc
EOF
```

From: <https://www.gamu.kr/dokuwiki/> -

Permanent link: https://www.gamu.kr/dokuwiki/linuxfromscratch/12.1/161-creating_the_etcinputrc_file?rev=1718085646

Last update: **2024/06/11 06:00**

